

ORIGINAL - PLASTIC MF BASE -

Original spare part



The cost-effective original spare parts

Discover our ORIGINAL signal lamps for printed circuit boards. These lamps with OSRAM's reliable OEM quality feature a wide product range and can be used for instrument and switch lighting.



Product datasheet

Technical data

Product information

Application (Category and Product specific)	Auxiliary lamp
---	----------------

General Product Information

Global order reference	2351MFX6
------------------------	----------

Electrical Data

Power input	1.32 W
Nominal voltage	12.0 V
Nominal wattage	1.20 W
Test voltage	13.5 V
Power input tolerance	±10 %

Photometric Data

Nominal luminous flux	7.5 lm
Luminous flux tolerance	±20 %

Physical Attributes & Dimensions

Diameter	5 mm
Product weight	0.77 g
Length	17.5 mm
Lamp base	BX8.4d-12.5

Colors & materials

Base color	Jet black
------------	-----------

Lifetime Data

Lifespan B3	600 hr
Lifespan Tc	3000 hr

Capabilities

Thickness of PCB	1.25 mm
Technology	AUX

Certificates & standards

ECE category	-
Approval marks – approval	-

Product datasheet

Environmental & Regulatory Information

Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACH)	
Date of declaration	09-07-2024
Primary article identifier	4062172046916 4008321096852 4008321011756
Candidate list substance 1	No declarable substances contained
Declaration no. in SCIP database	In work

Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4062172046930	ORIGINAL - PLASTIC MF BASE 2351MFX6		- x - x -	0.94 dm ³	

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.



OSRAM