

Lamps with glass wedge bases -

Original spare part



The cost-effective original spare parts

The ORIGINAL signal lamps with glass wedge bases are available as original spare parts for different lamp types. Discover these reliable lamps and OSRAM's proven high quality.



Product datasheet

Technical data

Product information

Application (Category and Product specific)	Auxiliary lamp
---------------------------------------------	----------------

General Product Information

Global order reference	2722
------------------------	------

Electrical Data

Power input	2 W
Nominal voltage	12.0 V
Nominal wattage	2 W
Test voltage	13.5 V
Power input tolerance	±15 %

Photometric Data

Nominal luminous flux	12 lm
Luminous flux tolerance	±20 %

Physical Attributes & Dimensions

Diameter	5 mm
Product weight	0.40 g
Length	20.0 mm
Lamp base	W2x4.6d

Lifetime Data

Lifespan B3	1300 hr
Lifespan Tc	4000 hr

Capabilities

Technology	AUX
------------	-----

Certificates & standards

ECE category	-
--------------	---

Environmental & Regulatory Information

Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACH)	
Date of declaration	09-07-2024

Product datasheet

Primary article identifier	4052899407251 4008321032249 4008321094803 4050300925783
Candidate list substance 1	No declarable substances contained
Declaration no. in SCIP database	In work

Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4008321094827	ORIGINAL - WEDGE BASE 2722		- x - x -	0.94 dm ³	
4008321140333	ORIGINAL - WEDGE BASE 2722		- x - x -	1.13 dm ³	

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.



OSRAM