

# Lamps with metal bases T4W

Original spare part



## The cost-effective original spare parts

ORIGINAL signal lamps with metal bases feature - like all ORIGINAL products from OSRAM - a reliable OEM quality. Due to the wide product range, the lamps can be used as original spare lamps for different applications.

# Product datasheet

## Technical data

### Product information

Application (Category and Product specific)	Auxiliary lamp
---	----------------

### General Product Information

Global order reference	3893
------------------------	------

### Electrical Data

Power input	4 W
Nominal voltage	12.0 V
Nominal wattage	4 W
Test voltage	13.5 V
Power input tolerance	±10 %

### Photometric Data

Nominal luminous flux	35 lm
Luminous flux tolerance	±20 %

### Physical Attributes & Dimensions

Diameter	8.8 mm
Product weight	1.86 g
Length	27.4 mm
Lamp base	BA9s

### Lifetime Data

Lifespan B3	600 hr
Lifespan Tc	1200 hr

### Capabilities

Technology	AUX
------------	-----

### Certificates & standards

ECE category	T4W
Approval marks – approval	E1 approval

### Environmental & Regulatory Information

Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACH)
---

## Product datasheet

<b>Date of declaration</b>	09-07-2024
<b>Primary article identifier</b>	4050300992631   4052899407381   4050300838489   4062172395984   4050300647609   4062172395960
<b>Candidate list substance 1</b>	No declarable substances contained
<b>Declaration no. in SCIP database</b>	In work

### Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4008321095626	ORIGINAL - METAL BASE T4W		- x - x -	0.94 dm <sup>3</sup>	
4008321140395	ORIGINAL - METAL BASE T4W		- x - x -	1.13 dm <sup>3</sup>	

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

#### Application advice

For more detailed application information and graphics please see product datasheet.

#### Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.



# OSRAM