

Lamps with glass wedge bases W21W

Original spare part



The cost-effective original spare parts

The ORIGINAL signal lamps with glass wedge bases are available as original spare parts for different lamp types. Discover these reliable lamps and OSRAM's proven high quality.



Product datasheet

Technical data

Product information

Application (Category and Product specific)	Auxiliary lamp
---	----------------

General Product Information

Global order reference	7505
------------------------	------

Electrical Data

Power input	25 W
Nominal voltage	12.0 V
Nominal wattage	21 W
Test voltage	13.5 V
Power input tolerance	±6 %

Photometric Data

Nominal luminous flux	460 lm
Luminous flux tolerance	±15 %

Physical Attributes & Dimensions

Diameter	20.0 mm
Product weight	6.80 g
Length	47.5 mm
Lamp base	W3x16d

Lifetime Data

Lifespan B3	400 hr
Lifespan Tc	600 hr

Capabilities

Technology	AUX
------------	-----

Certificates & standards

ECE category	W21W
--------------	------

Environmental & Regulatory Information

Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACH)	
Date of declaration	09-07-2024

Product datasheet

Primary article identifier	4052899324244 4062172396288 4052899324565 4062172396264 4052899417878 4062172345392
Candidate list substance 1	No declarable substances contained
Declaration no. in SCIP database	In work

Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4052899324268	ORIGINAL - WEDGE BASE W21W		- x - x -	2.57 dm ³	
4052899324572	ORIGINAL - WEDGE BASE W21W		- x - x -	2.31 dm ³	

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.



OSRAM