

# ORIGINAL MINIXEN

Original spare part



### The cost-effective original spare parts

ORIGINAL MINIXEN signal lamps for cars can be used for interior lighting as well as reading lights. Discover these original spare parts from OSRAM with reliable OEM quality and a wide product range.



## Product family datasheet

### Technical data

Product description	Product information	General Product Information	Electrical Data		
	Application (Category and Product specific)	Global order reference	Power input	Nominal voltage	Nominal wattage
ORIGINAL MINIXEN 2886X	Auxiliary lamp	2886X	6 W	12.0 V	6 W
ORIGINAL MINIXEN 3886X	Auxiliary lamp	3886X	6 W	12.0 V	6 W

Product description	Power input tolerance	Test voltage	Photometric Data	Physical Attributes & Dimensions	
			Nominal luminous flux	Lamp base	Length
ORIGINAL MINIXEN 2886X	±10 %	13.5 V	85 lm	W2.1x9.5d	26.8 mm
ORIGINAL MINIXEN 3886X	±10 %	13.5 V	80 lm	BA9s	27.4 mm

Product description	Diameter	Lifetime Data		Capabilities	Certificates & standards
		Lifespan B3	Lifespan Tc	Technology	ECE category
ORIGINAL MINIXEN 2886X	10.0 mm	400 hr	1000 hr	AUX	-
ORIGINAL MINIXEN 3886X	9 mm	400 hr	1000 hr	AUX	-

Product description	Environmental & Regulatory Information Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACH)			
	Date of declaration	Primary article identifier	Candidate list substance 1	Declaration no. in SCIP database
ORIGINAL MINIXEN 2886X	05-09-2024	4050300888668   4052899560604   4008321094667	No declarable substances contained	In work
ORIGINAL MINIXEN 3886X	05-09-2024	4050300885896   4008321095787	No declarable substances contained	In work

## Product family datasheet

### Application advice

For more detailed application information and graphics please see product datasheet.

### Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.

