

ORIGINAL - PLASTIC MF BASE -

Original spare part



The cost-effective original spare parts for motorcycles

With the ORIGINAL signal lamps for printed circuit boards, OSRAM offers a wide product range of original spare parts for motorcycles. These lamps provide OSRAM's reliable OEM quality and can be used for instrument and switch lighting.



Product datasheet

Technical data

Product information

Application (Category and Product specific)	Auxiliary lamp
---	----------------

General Product Information

Global order reference	2722MF
------------------------	--------

Electrical Data

Power input	2 W
Nominal voltage	12.0 V
Nominal wattage	2 W
Power input tolerance	±10 %
Test voltage	13.5 V

Photometric Data

Nominal luminous flux	10.2 lm
Luminous flux tolerance	±25 %

Physical Attributes & Dimensions

Lamp base	B8.5d
Length	21.6 mm
Diameter	5 mm
Product weight	1.20 g

Colors & materials

Base color	Lime green
------------	------------

Lifetime Data

Lifespan B3	1300 hr
Lifespan Tc	4000 hr

Capabilities

Thickness of PCB	1.6 mm
Technology	AUX

Certificates & standards

ECE category	-
--------------	---

Product datasheet

Environmental & Regulatory Information

Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACH)	
Date of declaration	09-07-2024
Primary article identifier	4008321057839 4008321096791
Candidate list substance 1	No declarable substances contained
Declaration no. in SCIP database	In work

Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4008321096814	ORIGINAL - PLASTIC MF BASE 2722MF		- x - x -	0.94 dm ³	

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.



OSRAM