## Product datasheet

# **OSRAM**

# ORIGINAL - METAL BASE T4W

Original spare part





#### The cost-effective original spare parts for motorcycles

Discover OSRAM's ORIGINAL signal lamps with metal bases high-quality original spare parts for motorcycle lamps. Due to the wide product range, the lamps can be used for different applications. Use these lamps for example as position and parking lights or for number plate and side position lights of your motorcycle.

# Product datasheet

#### Technical data

### **Product information**

Application (Category and Product specific)	Auxiliary lamp	
General Product Information		
Global order reference	3893	
Electrical Data		
Power input	4 W	
Nominal voltage	12.0 V	
Nominal wattage	4 W	
Power input tolerance	±10 %	
Test voltage	13.5 V	
Photometric Data		
Nominal luminous flux	35 lm	
Luminous flux tolerance	±20 %	

## **Physical Attributes & Dimensions**

Lamp base	BA9s
Length	27.4 mm
Diameter	8.8 mm
Product weight	1.86 g

## Lifetime Data

Lifespan B3	600 hr
Lifespan Tc	1200 hr

## Capabilities

Technology	AUX

#### **Certificates & standards**

ECE category

T4W

## Environmental & Regulatory Information

## Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACh)

Date of declaration

09-07-2024

# Product datasheet

Primary article identifier	4050300992631   4052899407381   4050300838489   4062172395984   4050300647609   4062172395960
Candidate list substance 1	No declarable substances contained
Declaration no. in SCIP database	In work

#### Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4008321095626	ORIGINAL - METAL BASE T4W		- x - x -	0.94 dm <sup>3</sup>	
4008321140395	ORIGINAL - METAL BASE T4W		- x - x -	1.13 dm³	

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

#### **Application advice**

For more detailed application information and graphics please see product datasheet.

#### Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.











