Product datasheet

OSRAM

ORIGINAL - METAL BASE R10W

Original spare part





The cost-effective original spare parts for motorcycles

Discover OSRAM's ORIGINAL signal lamps with metal bases high-quality original spare parts for motorcycle lamps. Due to the wide product range, the lamps can be used for different applications. Use these lamps for example as position and parking lights or for number plate and side position lights of your motorcycle.

Product datasheet

Technical data

Product information

Application (Category and Product specific) Auxiliary lamp		
General Product Information		
Global order reference	5008	

Electrical Data

Power input	10 W
Nominal voltage	12.0 V
Nominal wattage	10 W
Power input tolerance	±10 %
Test voltage	13.5 V

Photometric Data

Nominal luminous flux	125 lm
Luminous flux tolerance	±20 %

Physical Attributes & Dimensions

Lamp base	BA15s
Length	37.5 mm
Diameter	19.0 mm
Product weight	5.50 g

Lifetime Data

Lifespan B3	350 hr
Lifespan Tc	800 hr

Capabilities

Technology	AUX

Certificates & standards

ECE category

R10W

Environmental & Regulatory Information

Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACh)

Date of declaration

09-07-2024

Product datasheet

Primary article identifier	4052899407992 4052899407176 4050300925608 4062172396066 4008321163707 4062172396042 4008321186751 4050300838212 4008321355263
Candidate list substance 1	No declarable substances contained
Declaration no. in SCIP database	In work

Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4008321095299	ORIGINAL - METAL BASE R10W		- x - x -	1.89 dm³	
4008321140425	ORIGINAL - METAL BASE R10W		- x - x -	1.56 dm ³	

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Download Data

Ъ

File

ref_pim_amsp_product360degreeimages ORIGINAL R10W 5008

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.





0.0



<u>^</u>*



